

FIST-GC02

FIST Generic Closure Organizer


TELECOM OUTSIDE PLANT

FIST is Raychem's Fiber Infrastructure System Technology.

The generic closure FIST-GCO2 is the environmentally sealed enclosure for the fiber management system that provides the functions of splice and passive component integration in the external network.


The FIST-GCO2 has the following functions and features

- Single-ended design
- Base and dome are sealed with a clamp and 0-ring system
- 6 or 16 round entry/exit ports for drop cables and 1 oval port for looped cable
- The UMS (Universal Mounting System)
 profiles provide the foundation for
 mounting combinations of SOSA2 (Splice
 Only Sub-Assembly) and/or SASA2
 (Splitter Array Sub-Assembly) modules,
 which consist of a modular grooveplate
 and trays
- Compatible with most common cable types: e.g. loose tube, central core, ribbon fiber
- Uncut fibers can be stored as single circuits in trays and/or as cable elements in the storage space between the profiles. Storage baskets are available for mass storage of fibers of central core cable constructions




FIST-GC02

Dimensions and capacities



Key

- 1 Dome
- 2 Clamp
- 3 Base
- 4 Wrap-around grooveplates



		GCO2-BC6	GCO2-BD6	GCO2-BE6
Dimensions	L	488	566	700
in mm	Α	30	30	30
	B (B*/B**)	30 (20/13,5)	30 (20/13,5)	30 (20/13,5)
	С	82	82	82
	D	247	247	247
	D with clamp	285	285	285


	Fibers	Trays	Fibers	Trays	Fibers	Trays
Single Circuit Splicing Capacity	112	56	160	80	224	112
Single Element Splicing Capacity	336	28	480	40	672	56
R4/R8 Splicing Capacity	224	28	336	42	464	58
R12 Splicing Capacity	192	16	336	28	432	36

How to Order this product

1 Order one of the Application Kits

Application kits have been identified for an easy product selection and ordering. These kits contain all necessary items for a certain application and fiber count. Please refer to the FIST-GCO2 Ordering Guide for more information.

2 Order the closure and its accessories separately



For a list of accessories, please refer to the FIST-GCO2 Ordering Guide

Tyco, Raychem and FIST are trademarks

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, Tyco Electronics makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. Tyco Electronics' obligations shall only be as set forth in Tyco Electronics' Standard Terms and Conditions of Sale for this product and in no case will Tyco Electronics be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of Tyco Electronics products should make their own evaluation to determine the suitability of each such product for the specific application.

Tyco Electronics Raychem NV Telecom Outside Plant

Diestsesteenweg 692 3010 Kessel-Lo, Belgium Tel.: 32-16 351 011 Fax: 32-16 351 697 www.tycoelectronics.com

Tyco Electronics Corporation Telecom Outside Plant

8000 Purfoy Road Fuquay Varina NC 27526-9349 Tel.: 1-919-557-8900

Fax: 1-919-557-8598